

Part B8: Receivers, Transmitters, and Coil Sets

RECEIVER	PART OF SYSTEM	MADE BY	DATE
CBA-46000	RU-1	ARC	??-??-1931
CBY-46006	GF	ARC	06-25-1932
CBY-46012	GF/RU-2	ARC	06-25-1932
CBY-46012A	RU-2A	ARC	03-01-1935
CBY-46036	GF-1/RU-3	ARC	02-10-1934
CBY-46041	GF-2/RU-3A	ARC	02-10-1934
CBY-46046	RAJ	ARC	02-10-1934
CBY-46048	RU-4	ARC	06-29-1935
CBY-46048A	RU-5	ARC	??-??-1936
CBY-46048B	RU-6	ARC	??-??-1937
CBY-46048C	RU-10, RU-11 (early), RU-12 (early)	ARC	??-??-1938
CBY-46048D	RU-11 (late), RU-12 (late)	ARC	11-22-1939
CW -46048D	RU-18, RU-19	WEC _o	04-21-1941
CBY-46051	GF-3/RU-4A	ARC	06-29-1935
CBY-46051A	GF-4/RU-5A, GF-5/RU-7, GF-8/RU-13, GF-9/RU-14	ARC	02-23-1938
CW -46051A	GF-11/RU-16, GF-12/RU-17	WEC _o	04-21-1941
CBY-46064	GF-6/RU-8, GF-7/RU-9, GF-10/RU-15	ARC	02-23-1938

TRANSMITTER	PART OF SYSTEM	MADE BY	DATE
CBY-52004	GF, GF/RU-2	ARC	06-25-1932
CBY-52027	GF-1/RU-3	ARC	02-10-1934
CBY-52028	GF-2/RU-3A	ARC	02-10-1934
CBY-52063	GF-3/RU-4A	ARC	06-29-1935
CBY-52063A	GF-4/RU-5A, GF-5/RU-7, GF-6/RU-8, GF-7/RU-9, GF-8/RU-13, GF-9/RU-14, GF-10/RU-15	ARC	05-16-1936
CW -52063A	GF-11/RU-16, GF-12/RU-17	WEC _o	04-21-1941

```

=====
COIL          FREQ (kHz) RANGE  RECEIVER (Cxx-46###) OR TRANSMITTER (Cxx-52###)
=====

CBA-47000     Receiver coil set storage case
CBA-47001      225-14000      CBA-46000      (Set of 10 coils)

CBY-47019      224-   350      CBY-46006
CBY-47020      350-   545      CBY-46006
CBY-47021      545-   850      CBY-46006
CBY-47022      850-  1330      CBY-46006
CBY-47023     1330-  2040      CBY-46006
CBY-47024     2040-  3000      CBY-46006
CBY-47025     3000-  4500      CBY-46006
CBY-47026     4000-  6000      CBY-46006
CBY-47027     5400-  8100      CBY-46006
CBY-47028     8100-12500      CBY-46006

CBY-47029     Receiver coil set storage case

CBY-47030      224-   350      CBY-46012
CBY-47030A     200-   400      CBY-46012A only
CBY-47031      350-   545      CBY-46012
CBY-47032      545-   850      CBY-46012
CBY-47033      850-  1330      CBY-46012
CBY-47034     1330-  2040      CBY-46012
CBY-47035     2040-  3000      CBY-46012
CBY-47036     3000-  4500      CBY-46012
CBY-47037     4000-  6000      CBY-46012
CBY-47038     5400-  8100      CBY-46012
CBY-47039     8100-12500      CBY-46012

CBY-47042     6200-  7700      CBY-52004 MO
CBY-47043     6200-  7700      CBY-52004 ANT
CBY-47044     3150-  3850      CBY-52004 MO
CBY-47045     3150-  3850      CBY-52004 ANT

CBY-47064     6200-  7700      CBY-52027

CBY-47065      224-   350      A      CBY-46036, -46041, -46046, nt-46048(), -46051()
CBY-47066      350-   545      B      CBY-46036, -46041, -46046, nt-46048(), -46051()
CBY-47067      545-   850      C      CBY-46036, -46041, -46046, nt-46048(), -46051()
nt -47068      850-  1330      D      CBY-46036, -46041, -46046, nt-46048(), -46051()
nt -47069     1330-  2040      E      CBY-46036, -46041, -46046, nt-46048(), -46051()
CBY-47070     2040-  3000      F      CBY-46036, -46041, -46046, nt-46048(), -46051()
CBY-47071     3000-  4525      G      CBY-46036, -46041, -46046, nt-46048(), -46051()
nt -47072     4000-  6000      H      CBY-46036, -46041, -46046, nt-46048(), -46051()
CBY-47073     5400-  8100      I      CBY-46036, -46041, -46046, nt-46048(), -46051()
CBY-47074     8100-12500      J      CBY-46036, -46041, -46046, nt-46048(), -46051()
nt -47075     9050-13575      K      CBY-46036, -46041, -46046, nt-46048(), -46051()
CBY-47076      400-   600      L      CBY-46036, -46041, -46046, nt-46048(), -46051()
                3000-  4525      G
CBY-47077      400-   600      L      CBY-46036, -46041, -46046, nt-46048(), -46051()
                5200-  7700      M
CBY-47088     6000-  9050      N      CBY-46036, -46041, -46046, nt-46048(), -46051()

CBY-47089A     3000-  3675      CBY-52028, nt-52063()
CBY-47089B     3675-  4525      CBY-52028, nt-52063()
CBY-47089C     6000-  7350      CBY-52028, nt-52063()
CBY-47089D     7350-  9050      CBY-52028, nt-52063()

CBY-47092     Transmitter coil set storage case

```

```

----- Continued on Next Page -----

```

----- Continued from Previous Page -----

CBY-47098	224- 350	A	CBY-46036, -46041, -46046, nt-46048(), -46051()
	350- 545	B	
CBY-47099	5200- 7700	M	CBY-46036, -46041, -46046, nt-46048(), -46051()
nt -47105	195- 290	O	CBY-46036, -46041, -46046, nt-46048(), -46051()
	290- 435	P	
CBY-47106	400- 600	L	CBY-46036, -46041, -46046, nt-46048(), -46051()
nt -47107	540- 830	Q	CBY-46036, -46041, -46046, nt-46048(), -46051()
	3000- 4525	G	
nt -47108	540- 830	Q	CBY-46036, -46041, -46046, nt-46048(), -46051()
	5200- 7700	M	
nt -47112	400- 600	L	CBY-46036, -46041, -46046, nt-46048(), -46051()
	6000- 9050	N	
CBY-47127A	2000- 2500		CBY-52028, nt-52063()
CBY-47127B	2500- 3200		CBY-52028, nt-52063()
CBY-47127C	3000- 3675		CBY-52028, nt-52063()
CBY-47127D	3675- 4525		CBY-52028, nt-52063()
CBY-47128A	200- 400		CBY-46064
CBY-47128B	1000- 2000		CBY-46064
CBY-47128C	200- 390		CBY-46064
	2000- 3700		
CBY-47128D	200- 390		CBY-46064
	3100- 5600		
CBY-47128E	530- 1000		CBY-46064
	2000- 3700		
nt -47135	2000- 2500		CBY-52028, nt-52063()
nt -47136	2500- 3200		CBY-52028, nt-52063()
nt -47137	3000- 3675		CBY-52028, nt-52063()
nt -47138	3675- 4525		CBY-52028, nt-52063()
nt -47139	4000- 4900		CBY-52028, nt-52063()
nt -47140	4900- 6000		CBY-52028, nt-52063()
nt -47141	6000- 7350		CBY-52028, nt-52063()
nt -47142	7350- 9050		CBY-52028, nt-52063()
CBY-47143	200- 400	ZB	CBY-46064
CBY-47144	1000- 2000	ZE	CBY-46064
CBY-47145	200- 390	ZA	CBY-46064
	2000- 3700	ZF	
CBY-47146	200- 390	ZA	CBY-46064
	3100- 5600	ZG	
CBY-47146A	200- 394	ZR	CBY-46064
	3100- 5600	ZG	
CBY-47147	200- 390	ZA	CBY-46064
	5500- 9050	ZH	
CBY-47147A	200- 394	ZR	CBY-46064
	5500- 9050	ZH	
CBY-47148	530- 1000	ZD	CBY-46064
	2000- 3700	ZF	
nt -47202	2040- 3000	F	CBY-46036, -46041, -46046, nt-46048(), -46051()
	6000- 9050	N	
nt -47203	2040- 3000	F	CBY-46036, -46041, -46046, nt-46048(), -46051()
	3000- 4525	G	
nt -47204	540- 830	Q	CBY-46036, -46041, -46046, nt-46048(), -46051()
	2040- 3000	F	

Total: 81 coil sets, plus 3 coil set cases.