

AllStar user DTMF Commands

All commands begin with a star (*).

Command	Description	Example
1 <i>node</i>	Disconnect link	*11999
2 <i>node</i>	Monitor link (listen but don't send audio to the link)	*21999
3 <i>node</i>	Connect link in transceive mode (normal)	*31999
70	Speak system status	*70
81	Speak time of day and WX (12 hour clock)	*81
82	Speak time of day and WX (24 hour clock)	*82
A9	One time parrot (NOT the Monty Python Dead Parrot Skit!)	*A9 + msg

Note: The node number 1999 is a dummy node number and must be replaced with an actual AllStarLink assigned node number.

AllStar nodes may be found as a large list ordered by node number from node 2000 (the lowest active node number) to the latest assigned from:
<http://stats.allstarlink.org/>

Alternatively, AllStar nodes may be found on a state by state basis from:
<https://www.repeaterbook.com/repeaters/niche/index.php?mode=AllStar>

The voice from AllStar is named Allison and, no, she is not a psychoanalyst, marriage counselor, or late night friend! Her vocabulary is quite limited.

To use the parrot, key in *A9 and then speak your message. After you unkey and you hear the courtesy tone from the CAT-200B controller AllStar will play its recording of your voice. This is a handy way to hear how your station sounds through the repeater.

Have fun. I'm still learning quite a bit about this system and there are still some things to complete so there might be some bumps in the system's operation.

73, Nate