

OPA1611AID	G	1 (2)	S	\$3.60	4	BIPOLAR	Either	±2.25 or 4.5	±18 or 36	3.60	40.0	27.00	130	100	60,000	7.4	2.6	1.5	1.1	11.00	3.00	1.90	1.7000	0.000015	NR	Y	ULTRALOW-en noise, ultralow distortion, low-offset, drives 30mA (dual: OPA1612)		
OPA1612AIDR	G	2 (1)	S	\$5.17	6	BIPOLAR	Either	±2.25 or 4.5	±18 or 36	3.60	40.0	27.00	130	100	60,000	6.0	2.0	1.5	1.1	11.00	3.00	1.90	1.7000	0.000015	NR	Y	ULTRALOW-en noise, ultralow distortion, low-offset, drives 30mA (single: OPA1611)		
OPA1622IDRCR	?	2	VSON-10	\$4.22	1	BIPOLAR	Split	±2	±18	2.60	32.0	10.00	136	100	1,200	31.0	10.0	4.0	2.8	7.00	2.50	1.00	0.8000	0.000100	NR		SoundPlus, HiFi, low-noise, VSON-only, standby in, drives 32Ω and 600pF at 100-mW for headphones		
OPA1662AID	G	2 (4)	S,M,T	\$1.59	12	BIPOLAR	Either	±1.5 or 3.0	±18 or 36	1.50	22.0	17.00	114	500	600,000	6.3	3.6	3.3	3.3	20.00	7.00	2.00	1.0000	0.000060	NR+	Y	price/perf, BB, SoundPlus, low-Ibias, in=xFxA@1K, superlow-en noise, ultralow distortion, drives 30mA (headphone amp?) (quad: OPA1664)		
OPA1692IDR	?	2	S,V	\$1.15	4	BIPOLAR	Either	±1.75 or 3.5	±18 or 36	0.65	5.1	23.00		250	300,000	7.3	5.0	4.5	4.2	11.00	0.50	0.40	0.3700	0.000050	NR+	Y	SoundPlus, drives 50mA		
OPA211AIDR	G	1	S,V	\$5.41	4	BIPOLAR	Either	±2.25 or 4.5	±18 or 36	3.60	45.0	27.00	114	30	60,000	7.7	2.7	1.4	1.1	11.00	3.20	1.90	1.7000	0.000015	NR+	Y	ULTRALOW-en noise, low-offset, drives 30mA		
OPA2209AIDR		2 (1,4)	S,M,T,2	\$2.83	11	BIPOLAR	Either	±2.25 or 4.5	±18 or 36	2.50	18.0	6.40	132	35	1,000	8.0	3.3	2.3	2.2	1.60	0.65	0.50	0.5000	0.000025	NR+	Y	superlow-en/in noise, low-offset, decent output current (single: OPA209, quad: OPA4209)		
OPA2227PA	G	2 (1,4)	P,S	\$4.03	4	BIPOLAR	Split	±2.5	±18	3.70	8.0	2.30	160	10	2,500	6.9	3.7	3.2	3.0	6.50	2.00	0.80	0.4000	0.000050	NR?		BB, low-Ibias, superlow-en/in noise, very-low-offset (single: OPA227, quad: OPA4227)		
OPA2277PA	G	2 (1,4)	P,S	\$3.70	2	BIPOLAR	Either	±2 or 4	±18 or 36	0.79	1.0	0.80	134	10	500	17.5	9.3	8.1	8.0	0.50	0.24	0.20	0.2000	0.002000	NR?		a classic, very-low-offset and noise, drives 2kΩ and 1500pF, (single: OPA277, quad: OPA4277)		
RC4558P		2	P,S,T	\$0.21	100	BIPOLAR	Split	±5	±15	1.30	3.0	1.70	109	500	150,000					10.0	8.0	8.0				?	a classic, cheap, pretty-low-en noise, unknown-in noise (also see LM1458, MC1458)		
RC4560P		2	P,S	\$0.27	2	BIPOLAR	Split	±2	±16	2.20	15.0	5.50	100	500	40,000									0.050000	?		unknown-noise, drives 400Ω		
RC4580P		2	P,S	\$0.73	4	BIPOLAR	Split	±2	±16	3.00	12.0	5.00	110	500	100,000					8.5	7.0	6.5		0.000500	?		price/perf, low-en-noise, unknown-in noise, high out current (maybe headphone driver but high I _b)? (also see NJM4580, LM833, MC33078, NE5532, TS522, TL972)		
TL972IP	G	2 (1,4)	P,S,M,T,2	\$0.55	100	BIPOLAR	Single	+2.7	+12	2.00	12.0	5.00	80	1000	200,000	180.0	56.0	18.0	5.0					0.003000	?	Y	cheap, low-en noise BUT HIGH CORNER, unknown-in noise, low-voltage (single: TL971, quad: TL974)		
TLE2142IDR	G	2 (1,4)	P,S,T	\$2.06	2	BIPOLAR	Split	±2	±22	3.30	5.9	27.00	107	220	800,000	50.0	19.0	13.0	11.0	6.00	2.00	0.80	0.5000	0.010000	SDS	Y	pretty-low-en noise, drives 0.01uF (single: TLE2141, quad: TLE2144)		
TS522IDT		2	P,S	\$0.48	2	BIPOLAR	Split	±2.5	±15	4.00	15.0	7.00	100	900	250,000					15.0	5.0	4.5		0.5000	0.002000	?	~	cheap, low-noise (also see LM833, MC33078, NE5532, RC4580, TL972)	
uA741CP		1	P,S		2	BIPOLAR	Split	±5	±15	1.70	1.0	0.50	106	1000	80,000												?	a classic (~dual: LM1458, ~quad: LM348)	
AD8532ARZ		2 (1,4)	S,M,T,2,7	\$0.88	4	CMOS	Single	+2.7	+6	0.75	3.0	5.00		4000	5						0.20	0.05	0.0400		NR	Y	Y	low-Ibias, drives 250mA! (low-volt-hdphone amp?) (single: AD8531, quad: AD8534)	
AD8616ARZ	?	2 (1,4)	S,M,T,2	\$2.51	2	CMOS	Single	+2.7	+5	1.70	24.0	12.00	124	23	0					65.0	21.0	10.0		0.0500	0.002000	NR+	Y	Y	Ibias=200fA, drives 150mA (single: AD8615, quad: AD8618)
AD8692ARZ	?	2 (1,4)	S,M,T,2,7	\$1.40	2	CMOS	Single	+2.7	+6	0.95	10.0	5.00	108	400	0	120.0	40.0	12.0	8.0					0.0500	0.000600	?	Y	Ibias=200fA (single: AD8691, quad: AD8694)	
ADA4692-2ARZ	?	2 (4)	S,T	\$1.23	0	CMOS	Either	±1.35 or 2.7	±2.5 or 5	0.18	3.6	1.10	110	500	0	210.0	80.0	35.0	16.0					0.003000	?	Y	Ibias=500fA (quad: ADA4692-4)		
LM6211MF	?	1	2	\$2.10	0	CMOS	Single	+5	+24	1.05	17.0	5.50	110	100	0	100.0	34.0	13.0	6.0					0.0100	0.010000	?	~	Y	Ib=500fA, low-offset, pretty-low noise
LMC6462BIN		2 (4)	P,S	\$3.43	1	CMOS	Single	+3	+15.5	0.06	0.1	0.02	110	3000	10									0.0300	?	Y	Y	low-voltage/current, low-Ibias, drives 200pF, soic is cheaper (also see LMC6442 and LMC6482) (quad is LMC6464)	
LMC662AIN		2 (4)	P,S	\$1.33	2	CMOS	Single	+4.75	+15.5	0.40	1.4	1.10	110	3000	0					90.0	40.0	22.0		0.0002	0.010000	?	~	Y	Ibias=2fA, drives 600Ω (also see LMC662) (quad: LMC660)
LM7715MF	?	1 (2)	2,V	\$1.32	4	CMOS	Single	+1.8	+5	1.00	14.0	9.00	99	20	0	100.0	30.0	10.0	6.0				0.0100	0.001000	?	~	Y	Ib=50fA, low-offset, low-voltage, pretty-low noise (dual: LMP7716)	
LM7721MA	?	1	S*	\$3.86	0	CMOS	Single	+1.8	+5	1.30	17.0	11.00	120	50	0	120.0	40.0	13.0	7.0				0.0100	0.000700	?	~	~	super-low-Ib=3fA, low-offset, low-voltage, pretty-low noise, non-std pinout	
LMV751M5		1	2	\$1.54	2	CMOS	Single	+2.7	+5	0.50	4.5	2.00	120	50	2	50.0	16.0	8.0	7.0				0.0100	?	~	~	low-Ibias, low-offset, low-noise, drives 1000-pF, drives 8mA		
LMV797MM		2 (1)	V,2	\$1.26	2	CMOS	Single	+1.8	+5.5	1.10	14.0	8.50	92	100	0	100.0	29.0	10.0	5.8				0.0100	0.010000	?	~	~	Ibias=100fA, low-offset, low-voltage, pretty-low noise, drives 60mA (low-voltage headphone amp?) (single: LMV796)	
LPC662AIN		2 (4)	S		0	CMOS	Single	+5	+15	0.05	0.4	0.11	120	3000	0					115.0	50.0	42.0		0.0002	0.010000	?	~	~	Ibias=2fA, low-current (also see LMC662) (quad: LPC660)
LTC6078CM	Y	2 (4)	M,T	\$1.98	0	CMOS	Single	+2.7	+5.5	0.06	0.8	0.05		7	0	75.0	30.0	19.0	18.0					0.0006	?	Y	Y	Ibias=200fA, kinda-low-en noise, low-voltage/current, very-low-offset (quad is LTC6079)	
LTC6241CS8	Y	2 (1,4)	S,T,2	\$1.66	2	CMOS	Single	+2.8	+6	1.80	18.0	10.00		40	0	52.0	16.0	8.0	7.0					0.0006	?	Y	Y	Ibias=200fA, in=0.6fA@1K THEN RISES, pretty-low-en noise, low-voltage, low-offset (single: LTC6240, quad: LTC6242) (in Itsipice) (also see OPA2376)	
OPA1652AID	G	2 (4)	S,M,T	\$1.61	12	CMOS	Either	±2.25 or 4.5	±18 or 36	2.00	18.0	10.00	114	500	10	120.0	34.0	11.0	4.5					0.0030	0.000050	NR+	Y	price/perf, SoundPlus, low-Ibias, low-en noise BUT HIGH CORNER, ultralow distortion, drives 30mA (headphone amp?) (quad: OPA1654)	
OPA1656IDR	?	2	S	\$1.84	35	CMOS	Either	±2.25 or 4.5	±18 or 36	3.90	53.0	24.00	150	500	10	120.0	34.0	11.0	4.3					0.0060	0.000150	NR+	Y	new BB, en=2.9@10kHz (lower than OPA1652) (also see OPA1652/1678/1688/2134)	
OPA1671IDCKT	G	1	7	\$0.87	4	CMOS	Either	±0.85 or 1.7	±2.75 or 5.5	0.94	13.0	5.00	113	250	10	175.0	55.0	20.0	7.0					0.0047	0.000350	NR+	Y	price/perf, low-Ibias, decent-en noise BUT HIGH CORNER, ultralow distortion	
OPA1678IDR	G	2 (4)	S,V	\$0.44	102	CMOS	Either	±2.25 or 4.5	±18 or 36	2.00	16.0	9.00	114	500	10	120.0	35.0	12.0	4.5					0.0030	0.000100	NR+	Y	cheap, low-Ibias, low-en noise BUT HIGH CORNER (quad: OPA1679), ultralow distortion (see LM833 etc.)	
OPA1688IDR	G	2 (4)	S	\$1.06	110	CMOS	Either	±2.25 or 4.5	±18 or 36	1.65	10.0	8.00	130	250	10	120.0	34.0	14.0	8					0.0018	0.000350	NR+	~	Y	BB, SoundPlus, low-Ibias, decent-en noise BUT HIGH CORNER (quad: OPA1689)
OPA2171AIDR	G	2 (1,4)	S,T,V,2	\$1.20	12	CMOS	Either	±1.35 or 2.7	±18 or 36	0.48	3.0	1.50	130	250	8	200.0	65.0	25.0	14.0					0.000200	NR+	~	Y	low-Ibias, drives 300pF (single: OPA171, quad: OPA4171)	
OPA2192IDR	G	2 (1,4)	S,V,T,2	\$3.00	2	CMOS	Either	±2.25 or 4.5	±18 or 36	1.00	10.0	20.00	134	5	5	88.0	27.0	10.0	6.0					0.0015	0.000080	NR+	Y	Y	low-Ibias, very-low-offset, low-en noise but depends on Vcm (single: OPA192, quad: OPA4192)
OPA2313ID		2 (1,4)	S,M,T,2,7	\$0.98	2	CMOS	Either	±0.9 or 1.8	±2.75 or 5.5	0.05	1.0	0.50	110	500	0	125.0	50.0	30.0	25.0					0.0050	0.004500	NR+	Y	Y	Ibias=200fA, very-low-voltage/current (single: OPA313, quad: OPA4313)
OPA2314AID	GN	2 (1,4)	S,V,T,2,7	\$1.10	2	CMOS	Either	±0.9 or 1.8	±2.75 or 5.5	0.15	3.0	1.50	100	500	0		50.0	17.0	14.0					0.0050	0.001000	NR+	Y	Y	Ibias=200fA, very-low-voltage, lowish-en noise (single: OPA314, quad: OPA4314)
OPA2316IDR		2 (1,4)	S,M,T,2,7	\$1.07	4	CMOS	Either	±0.9 or 1.8	±2.75 or 5.5	0.40	10.0	6.00	96	500	5	210.0	64.0	21.0	11.0					0.0013	0.000800	NR+	Y	Y	very-low-voltage, lowish-en noise (w/shutdown: OPA2316S, single: OPA316, quad: OPA4316)
OPA2340PA	G	2 (1,4)	P,S,V,2	\$3.43	0	CMOS	Single	+2.7	+5.5	0.80	5.5	6.00	114	150	0	500.0	160.0	65.0	25.0					0.0030	0.000700	?	Y	Ibias=200fA, in=3fA@1K RISING (corner at 10), low-voltage, pretty-low-offset (single: OPA340, quad: OPA4340)	
OPA2348AIDR	G	2 (1,4)	S,V,T,2,7	\$0.70	3	CMOS	Single	+2.1	+5.5	0.05	1.0	0.50	98	1000	1	880.0	270.0	70.0	33.0					0.0040	0.002300	?	Y	Y	Ibias=500fA, in=4fA@1K RISING (corner at ~400), low-voltage/current (single: OPA348, quad: OPA4348)
OPA2350UA		2 (1,4)	P,S,T,V	\$3.18	2	CMOS	Either	±1.35 or 2.7	±2.75 or 5.5	5.20	38.0	22.00	120	150	1					4fA @ 10kHz				0.00					

LT1113CN8	Y	2	P,S	\$4.18	2	JFET	Split	±5	±20	5.30	5.6	3.90	130	550	320	50.0	17.0	6.2	4.5	0.0100	0.000600	NR+	low-en noise, drives 1000pF (~single: LT1792)
LT1792CN8	Y	1	P,S	\$2.99	2	JFET	Split	±5	±20	4.20	5.6	3.40	132	400	300	28.0	8.3	4.9	4.2	0.0100	0.000600	NR+	low-en noise, drives 1000pF (~dual: LT1113)
OPA1642AID	G	2 (1,4)	S,V	\$1.70	33	JFET	Either	±2.25 or 4.5	±18 or 36	1.80	11.0	20.00	134	1000	2	15.0	8.0	5.8	5.1	0.0008	0.000050	NR+	Y SoundPlus, low-Ibias, low-en noise, ultralow distortion (single: OPA1641, quad: OPA1644)
OPA2130UA	G	2 (1,4)	S	\$4.81	2	JFET	Split	±2.25	±18	0.60	1.0	2.00	120	200	5	96.0	33.0	18.0	16.0	0.0040		NR?	BB, low-Ibias, in=4FA@1K THEN RISES, pretty-low-offset, kinda-low-en noise (single: OPA130, quad: OPA4130)
OPA2132PA	G	2	P,S	\$4.99	1	JFET	Split	±2.5	±18	4.00	8.0	20.00	130	500	5	84.0	26.0	11.0	8.0	0.0030	0.000080	NR?	BB, low-Ibias, in=3FA@1K THEN RISES, low-en noise BUT HIGH CORNER, ultralow-distortion, low-offset (single: OPA132)
OPA2134PA	G	2	P,S	\$3.52	11	JFET	Split	±2.5	±18	4.00	8.0	20.00	120	500	5	85.0	27.0	12.0	8.0	0.0030	0.000080	NR+	~ a classic, BB, SoundPlus, low-Ibias, in=3FA@1K THEN RISES, low-en noise BUT HIGH CORNER, low-offset, decent current drive (headphone driver?), ultralow-distortion (single: OPA134)
OPA2137PA	GN	2 (1,4)	P,S,M,2	\$1.63	0	JFET	Either	±2.25 or 4.5	±18 or 36	0.20	1.0	3.50	94	2500	4	60.0	45.0	45.0	45.0	0.0012	0.050000	NR+	BB, low-Ibias (single: OPA137, quad: OPA4137)
OPA2604AP	GN	2	P		4	JFET	Split	±4.5	±24	5.50	20.0	25.00	100	1000	100	65.0	25.0	15.0	11.0	0.0060	0.000300	?	obsolete, BB, lowish-en noise, drives 600Ω
OPA604AP	GN	1	P	\$2.43	2	JFET	Split	±4.5	±24	5.50	20.0	25.00	100	1000	100	65.0	25.0	15.0	11.0	0.0060	0.000300	?	BB, lowish-en noise, drives 600Ω
OPA827AID	?	1	S,V	\$8.08	2	JFET	Split	±4	±18	4.80	22.0	28.00	126	75	3	18.0	7.2	4.4	4.0	0.0022	0.000040	NR+	ultra-low-en (for fet) (also see AD743, ADA4625-x)
TL072ACP	GN	2 (1,4)	P,S,T	\$0.64	26	JFET	Split	±5	±15	1.40	3.0	13.00	106	3000	65		44.0	26.0	18.0	0.0100	0.003000	YCM	a classic, good for general audio, kinda-low-en noise, drives ~3kΩ, (B ver is lower offset)
TLV2462CP	?	2 (1,4)	P,S,M,T,2	\$1.85	2	JFET	Either	±1.35 or 2.7	±3 or 6	0.50	6.4	1.60	90	500	4,400		23.0	16.5	11.5	0.1300	0.006000	?	Y Y low-voltage, low-power, kinda-low-en-noise, drives 80mA (single: TLV2460, quad: TLV2464)
TLC272BIP	?	2	P,S	\$1.02	4	LINCMOS	Single	+2.7	+8	0.70	2.0	3.00	87	230	0	370.0	130.0	48.0	25.0			?	Ibias=600fA
TLV2262AIP	?	2 (4)	P,S,T	\$3.43	0	LINCMOS	Single	+3	+16	0.40	0.7	0.55		300	1				12.0	0.0006		?	~ Y (quad is TLV2264)
TLC2272ACP	G	2 (4)	P,S,T	\$3.43	2	LINMOS	Either	±2.2 or 4.4	±8 or 16	2.40	2.0	3.60	91	300	1	160.0	50.0	17.0	9.0	0.0006	0.004000	?	Y low-Ibias (improves TLC272) (quad: TLC2274)
GET						GET																	

A
 Om is favorite
 Gn is nice
 Yel is interesting
 Blu is special
 Red is obsolete

A
 P=PDP, S=SOIC,
 M=MSOP, V=VSSOP,
 2=SO23, 5=SO1533
 7=SC70

A
 0.0001% = 1ppm = 20log(0.0001/100) = -120dB
 0.001% = 10ppm = 20log(0.001/100) = -100dB
 0.01% = 100ppm = 20log(0.01/100) = -80dB

A
 NR = no reversal to rails
 NR+ = no reversal to a bit above rails
 RCM = reversal beyond common-mode
 SDS = see data sheet