

# engineering data service

sylvania 6BW4 12BW4

# MECHANICAL DATA

Bulb .														•					<b>T-61</b> /2
Base .											E9-1	N	Air	nia	tur	e l	But	ton,	9-Pin
Outline																			. 6-3
Basing																			9DJ
Cathode														С	oat	ed	U	nip	otenial
Mountin	g	Pos	siti	on	•	•	•	•		•			•	•	•		•		Any

### ELECTRICAL DATA

#### HEATER CHARACTERISTICS

	6 <b>BW4</b>		12BW4
Heater Voltage <sup>3</sup> AC or DC	 . 6.3		12.6 Volts
Heater Current	 . 900		450 Ma
Maximum Heater Cathode Voltage Heater Negative, DC		450	Volts

#### RATINGS (Design Center Values)<sup>1</sup>

Rectifier Service			
Peak Inverse Plate Voltage	1275	Volts	Max.
A C Plate Supply Voltage Each Plate, R MS			
(See Rating Chart I)	450	Volts	Max.
DC Output Current See Rating	Chart I		
Steady State Peak Plate Current Each Plate			
(See Rating Chart II)	350	Ma	Max.
Transient Peak Plate Current Each Plate			
(See Rating Chart III)	2.0	Ampe	res Max.
		-	

#### AVERAGE CHARACTERISTICS

Tube Voltage Drop								
Tube Conducting:								
100 Ma Each Plate .							40	Volts

#### TYPICAL OPERATION

Full Wave Rectifier Capacito	or .	Inpu	ut	Fil	ter	r					
AC Plate Supply Voltage Each Pla	ate,										
$RMS^2$	•	•							•	. 325	Volts
Filter Input Capacitor	•			•					•	. 40	μf
Effective Plate Supply Resistance											
Each Plate		•				•	•	•	•	. 82	Ohms
DC Output Current	•	•		•	•	•	•	•		. 100	Ma
DC Output Voltage at Filter Inpu	t.	•	•	•	•	•	•	•	•	. 330	Volts

#### Full Wave Rectifier - Choke Input Filter

#### NOTES:

1. See "Interpretation of Rating Charts".

2. A C plate voltage is measured without load.

# QUICK REFERENCE DATA

The Sylvania 6BW4 and 12BW4 are miniature cathode type full wave rectifiers featuring relatively high output current capabilities.

The 12BW4 is intended primarily for use in auto receivers having a 12 volt heater supply.





#### SYLVANIA ELECTRIC PRODUCTS INC.

#### RADIO TUBE DIVISION EMPORIUM, PÀ.

Prepared and Released By The TECHNICAL PUBLICATIONS SECTION EMPORIUM, PENNSYLVANIA

SEPTEMBER 1955

PAGE 1 OF 5

#### NOTES: (Continued)

SYLVANIA

6BW4

28W4

PAGE 2

3. The 12BW4 is intended to be used in automotive service from a nominal 12 volt battery source. The heater is therefore designed to operate over the 10.0 to 15.9 voltage range encountered in this service. The maximum ratings of the tube provide for an adequate safety factor such that the tube will withstand the wide variation in supply voltages.

#### INTERPRETATION OF RATING CHARTS

Rating Charts I, II and III represent boundary conditions beyond which operation of the 6BW4 and 12BW4 is not permitted. With the aid of simple laboratory measurements and the use of the three Charts, any application may be analyzed for proper rectifier type operation.

The boundaries of Rating Chart I are based on limits of supply voltage, plate dissipation and output current. These boundaries differ, depending upon the type of filter used. With capacitor input, operation is confined to the area bounded by FAEDG while for choke input, the entire area bounded by FABCDG may be used.

The boundary of Rating Chart II defines the limit of steady-state peak current. Operation within the boundary is permitted.

Rating Chart III defines the minimum value of effective plate supply resistance, per plate, for any given plate voltage supply which will assure that the surge currents are within a safe value.

$$\mathbf{R}_{s} = \mathbf{N}^{2}\mathbf{R}_{pri} + \mathbf{R}_{sec} + \mathbf{R}_{a}$$

Where: N = Voltage step up ratio of plate transformer.

 $R_{pri} = DC$  resistance of transformer primary.

 $R_{sec} = Average DC$  resistance of transformer secondary per section.

 $R_a = Added$  series resistance.

For any application, each Chart should be consulted. On *all* Charts the points of operation should fall within the proper boundaries.

Plate supply voltages are measured with the rectifier tube non-conducting, i.e., with the transformer unloaded. This unloaded voltage is used when calculating rectification efficiency.

The rectification efficiency is defined as:

DC Output Voltage

 $\sqrt{2}$  (RMS Supply Voltage Per Plate)

The DC output voltage is measured at the input to the filter.

SYLVANIA 6BW4 12BW4 page 3

# RATING CHART I



SYLVANIA 6BW4 12BW4 PAGE 4

RATING CHART II



SYLVANIA 6BW4 12BW4 page 5

RATING CHART III

